

YB4835 Digital AC Ammeter Current Meter AC 10A 30A 50A 100A



Feature:

Current range: AC 0-10A 0-30A 0-50A 0-100A

Supply voltage range: AC 80V-300V (can be customized AC160V-500V)

Measurement accuracy: $1\% \pm 2$ words

Display: 0.56 inch LED digital tube display

Measuring speed: about 2 times per second

Dimensions: 70*40*30 mm

Installation size: 68*38mm

Supply line length: about 150mm

"Split" transformer lead length: about 100mm

Display colors: red green blue

Working temperature: $-10^{\circ}\text{C} \sim 65^{\circ}\text{C}$

resolution ratio: 0.01A

Usage: Ampere Meter tester



With Back Cover

Extreme working conditions:

Operating temperature: $-10 \sim +50^{\circ}\text{C}$

Working pressure: 80 ~ 106kPa

Working humidity: 10 ~ 80% (no condensation)

Sun exposure: no direct exposure

Package included :

1*AC Digital Ammeter

RUI CHI